Xerox Phaser 3610 Configuration Guide

UF Health – Xerox Private Data



Document Revision History

By	Date	Version Number	Description of changes
Allen Messick	02-03-2014	1.0	initial
Allen Messick	02-11-2014	1.1	Added UF Health changes

Page 2 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

Phaser 3610 CetnreWare Information Services

Before you begin:

• Locate your printer IP address using the Configuration Report or the Machine Status button

1. At your computer, open a Web browser, type the IP address of the printer in the address field, then press **Enter** or **Return**.

Disable Protocols

FTP

1. Select FTP.

Internet Services Phaser 3610		н	? elp
Status Jobs	Properties FTP Enable FTP:	Support	
Billing Bettings Billing Bettings Billing Bettings Billing Billing Billing Billing Billing Billing Billing Billing Billing Bil	Connection Timeout: Password: Re-enter Password:	16 seconds (1 ~ 10	00)
Orregiou	Sa	Ve Changes Discard Changes	
SAMP DEmail Settings	-		
		>	erox 🌍

- 2. Uncheck the Enable FTP checkbox.
- 3. Click Save Changes.

Page 3 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

SMB

1. Select SMB

nternet Services			
ternet Services		<u></u>	
haser 3610		Help	
Status Jobs	Properties Suppor	t	
Detector Settings	•		
Trou Settings	SMB		
Resets			
Internet Services Setting	Enable SMB:	TCP/IP , V NetBEUI	
Physical Connection	Host Name:	XRX9C934E23E044	
Ethernet		Comparison where the second seco	
USB Settings	workgroup:	WORKGROUP	
Protocols	Maximum number of sessions:	5	
	Unicode Support:	*Disabled 💌	
Port9100	Auto Master Mode:	*Enabled	
IPP (Internet Printing Pro	Deserved Secondination		
- Dwsd	Password Encryption:	*Enabled 🔻	
DETP	Print Timeout:	600 seconds (60 ~ 3600)	
	Non-Print Timeout:	180 seconds (60 ~ 3600)	
Bonjour (mDNS)		accura (oo 3000)	
DEmail Cathings			
CHITTP -	Save Chang	es Discard Changes	
		VOCOV (S)	
		xerox 🔊	

- 2. Uncheck the Enable SMB checkbox.
- 3. Click Save Changes.

Bonjour (mDNS)

1. Select Bonjour (mDNS).

Interne Phas	et Services ser 3610		P Help
Stat	us Jobs <u>kem Settings</u> <u>k Settings</u> <u>/ Settings</u> ets	Properties Bonjour (mD	Support NS)
Dinte	rnet Services Setting cal Connection ernet Settings cols	Enable Bonjour (mDNS): Host Name: Printer Name:	XRX9C934E23E044 Xerox Phaser 3610 (23:E0:44)
- DLPR - DLPR - DPort - DIPP	/IP 9100 (Internet Printing Pro	wide-Area Bonjour:	Changes Discard Changes
- DSNM	jour (mDNS)		Û
	r i <u>il Settings</u> P		
			xerox 🅤

Page 4 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

- 2. Uncheck the Enable Bounjour (mDNS) checkbox.
- 3. Click Save Changes.

Disable USB Port

1. Select USB Settings.

Internet Services		P	
Status Jobs	Properties Support		
Dinternet Services Setting: DPhysical Connection DEthernet DSB Settings	USB Port: PS Data Format: Job Timeout:	*Auto 30 seconds (0:Off, 5 ~ 300)	
- DLPR - DPort9100 - DLPP (Internet Printing Pro- - DWSD - DFLP	Save Changes	Discard Changes	
Deniour (mDNS) Denniour (mDNS) Dennail Settings DHTTP T			
* <u> </u>		xerox 🌍	I

- 2. Uncheck the USB Port Enabled checkbox.
- 3. Click Save Changes.

Page 5 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

Enable SNMPv3

1. Select Security: Administrator Security Settings.

Internet Services Phaser 3610	? Help
Status Jobs LSNIF DairPrint Cocole Cloud Print OPrinter Fonts Page Description Language PPCL Settings DDF Settings Cocole Settings Cocole Settings DES Settings D	Properties Support Administrator Security Settings Enable Administrator Mode: User Name: Password: Verify Password: Access denial by the authentication failure of the Administrator : 5 (0:Disable, 5 ~ 255) Save Changes Discard Changes
CBSL CBSL CBCstration CBCstrat	xerox 🔊

- 2. Place a check in the box to Enable the Administrator Mode.
- 3. Enter 1111 in the Password box and in the Verify Password box.
- 4. Click Save.
- 5. Select Secure Settings.

Status Jobs Properties Support Printing Panel Lock / Network Authentication Panel Lock Set: Enable PDOF Sattinas Panel Lock Set: Enable New Passcode: Enable Poscurity Software Download: Enable Enable Enable Phost Access List (IPV4) Software Download: Enable Enable Phost Access List (IPV4) Software Information: TIp Address Tip Address	
Status Jobs Properties Support ArbErdit Cooole Cloud Print Secure Settings Printer Fonts Panel Lock / Network Authentication Page Description Language Panel Lock Set: Enable Panel Lock Set: Postitinas Re-enter Passcode: Security Software Download: Ibbs Access List (IPv4) Show Network Information:	
SNUP Daroale Cloud Print Booole Cloud Print Printing Printer Fonts Page Description Language Panel Lock / Network Authentication Page Description Language Panel Lock / Network Authentication Panel Lock / Network Information: Panel Lock / Network Information:	
AirPrint Secure Settings Printing Panel Lock / Network Authentication Printing Panel Lock / Network Authentication Proge Description Language Panel Lock Set: PDF Settings Panel Lock Set: PDF Settings Re-enter Passcode: Security Security Security Security Settings Software Download: Image: Software Download: Enable Image: Software Download: Enable Software Download: Enable	
Geodie Cloud Print Secure Settings Printer Fonts Panel Lock / Network Authentication Page Description Language Panel Lock Set: Enable Panel Lock Set: Enable Panel Lock Set: PDF Settinas Re-enter Passcode: Security Settinas Software Download: Index Settinas Software Download: Index Settinas Software Download: Index Settinas Software Download:	
Printing Panel Lock / Network Authentication Prage Description Language Panel Lock / Network Authentication Page Description Language Panel Lock Set: Pointing Panel Lock Set: Pointing New Passcode: PSS Settings Re-enter Passcode: Security Software Download: Indiministrator Security Settings Software Download:	
Printer Fonts Panel Lock / Network Authentication Printer Fonts Panel Lock / Set: Panel Lock Set: Enable PDF Settinas New Passcode: PS Settinas Re-enter Passcode: Security Settinas Software Download: Image: Software Download: Enable	
Page Description Language Panel Lock Set: Page Description Language Panel Lock Set: PDF Settings New Passcode: PDF Settings Re-enter Passcode: Security Software Download: Didst Access List (IPv4) Software Download: DipSec Show Network Information:	
PCC. Settings New Passcode: PDF Settings Re-enter Passcode: PS Settings Re-enter Passcode: Security Software Download: Indiministrator Security Settings Software Download: Show Network Information: *IP Address	
PDF Settings New Passcode: PS Settings Re-enter Passcode: PS Security Settings Software Download: Image: Software Download: Enable	
Descurity Re-enter Passcode: Security Software Download: Indexcess List (IPv4) Enable	
Security Se	
Image: Secure Settings Software Download: Enable Host Access List (IPv4) Show Network Information:	
Secure Settings Software Download: Enable	
Distances list (IPv4) Dipsec Show Network Information:	
Show Network Information: *IP Address	
Show Network Information: *IP Address	
Device Memory Data Encryption: Device Memory Data Encryption	
E Registration	
Login Attempts : *Off	
Supplies Assistant	
m · ·	

Page 6 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1 6. Click the Device Memory Data Encryption link.

Internet Services Phaser 3610	P Help	
Status Jobs Def Settings Status Status Def Settings Def Settings Status Def Settings Def Settings Status Def Settings Status Def Settings Def Settings Status Def	Properties Support Device Memory Data Encryption Encryption *1 : Encryption key *1 : Re-enter Encryption Key: *1 All stored documents will be deleted after you change Data Encryption Settings.	
Secure Settings Discure Settings Discure Settings Discure Settings Discure Settings State Solutions Registration Meter Assistant Supplies Assistant	Save Changes Discard Changes	
	xerox 🌒	

- 7. Click in the checkbox to Enable Encryption.
- 8. Enter a random value in both the Encryption Key boxes.
- 9. Click Save Changes.
- 10. Select SSL

Internet Services Phaser 3610		P
Status Jobs	Properties Support	
Printer Fonts Page Description Language PCL Settings PDF Settings PS Settings Security	Enable SSL: Port Number: SMTP - SSL/TLS Communication: Verify Remote Server Certificate:	 ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
Administrator Security Se Secure Settings Host Access List (IPv4) DPsec P803 1v	Machine Digital Certificate Certificate Management: Delete All Certificates:	Certificate Management Delete All Certificates
BOLLIX BOSHart esolutions PRegistration PMeter Assistant CSupplies Assistant	Save Changes	Discard Changes
< +		xerox 🄊

Page 7 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

- 11. Click the Certificate Management link.
- 12. In the Validity box enter **5000**.

Internet Services Phaser 3610	2 Help	
Status Jobs	Properties Support	
LISNIP		
AirPrint	Cuesta New Certificate	
Google Cloud Print	Create New Certificate	
© Printing	· · · · · · · · · · · · · · · · · · ·	
Printer Fonts	Public Key Method: *RSA/SHA-256 -	
Page Description Language	Public Key Size: *2048 bits •	
PCL Settings		
PDF Settings	Issuer: XRX9C934E23E044	
PS Settings	Validity: 5000 day(s) (1 ~ 9999)	
By Security		
Commission Security Se		
Blact Access List (IBud)	Generate Signed Certificate Back	
DIPERS	Λ.	
- PRO2 1x	1 U	
- Deel	-	
SMart eSolutions		
Registration		
Meter Assistant		
Supplies Assistant		
• m •		
	xerox 🌒	

- 13. Click Generate Signed Certificate.
- 14. Select checkbox to Enable SSL.

The second second	
Internet Services	2
Dhasaa 2010	Help
Phaser 3610	
Status Jobs Properties	Support
I I LISNIP	
AirPrint	
Google Cloud Print 55L	
D Printing	
Printer Fonts Enable SSL:	
Port Number:	443 (443, 8000 ~ 9999)
PDF Settings SMTP - SSL/TLS Cor	munication: *STAPTTLS (if Available) -
PS Settings	STACTES (I Available)
Security Verify Remote Serve	er Certificate: Enabled
Administrator Security Se	
Secure Settings Machine Digital	Certificate
Certificate Managem	ent: Certificate Management
Delete All Certificate	s: Delete All Certificates
- DSSI	
Del SMart eSolutions	Save Changes Discard Changes
Registration	
" Meter Assistant	∩
Supplies Assistant	
۲ m ه	
	xerox 🐔
	Acton

15. Click Save Changes.

Page 8 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

16. Select SNMP.

Internet Services Phaser 3610		? Help
Status Jobs	Properties Support SNMP SNMP Configuration	
DETP DSMB DBoniour (mDNS) DSMMP (CONS) DEmail Settings DHTTP DProxy Server DSMP	Enable SNMP: Enable SNMP v1/v2c Protocols Enable SNMP v3 Protocol Note: Enable either SNMP v1/v2c or SNMP v3. Enable SSL to edit the SNMP v3 protocol.	Edit SNMP v1/v2c Properties Edit SNMP v3 Properties
SNTP DAIrPrint Google Cloud Print Printer Fonts Page Description Language	Save Changes	Discard Changes
CPCL Settings		xerox 🔊

- 17. Uncheck Enable SNMP v1/v2 Protocols.
- 18. Check Enable SNMP v3 Protocol.
- 19. Click Save Changes.
- 20. Click Restart.

Note: The remainder of the SNMPv3 Configuration will be completed at Install.

s Jobs Properties Support A CLOO Internet Printing Pro Settings have been changed. Restart system for new settings to take effect. Restart Back Back Settings Back B	Status Jobs Properties Support Durp: Intermet Printing Pro Dwss Derrig Derrig	Internet Services	P	
g er Fonts	Page Description Language DPDC Settings T DPDF Settings T T T T T T T T T T T T T T T T T T T	Phaser 3610 Status Jobs DParts 100 DProt9100 DPP (Internet Printing Pro ONE DETP Density 100 Density 100 Density 100	Properties Support Settings have been changed. Restart system for new settings to take effect. Restart Back Back	

Page 9 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

21. Return to SNMP.

Internet Services		? Help
Status Jobs	Properties Support	
EURP LINEERNEE Printing Pro EWSD EFTP ESMB	SNMP Configuration	V
Boniour (mDNS) Boniour (mDNS) BNMP Benail Settings BHTIP Proxy Server	Enable SNMP v1/v2c Protocols Enable SNMP v3 Protocol Note: Enable either SNMP v1/v2c or SNMP v3. Enable Sto edit the SNMP v3 protocol.	Edit SNMP v1/v2c Properties Edit SNMP v3 Properties
	Save Changes	Discard Changes
Printer Fonts Page Description Language PCL Settings		
m +		
		xerox 🄊

- 22. Click the Edit SNMP v3 Properties link.
- 23. Click Account Enabled checkbox.

Phaser 3610		Help		
Status Jobs ULER Derrs100 DIPP (Internet Printing Pro DKSD DFP DSHM Deniour (mDNS) DSNMP Deniour strings DHTP DSNMP Deniour (mDNS) DSNMP Description Language DPC. Settings D'''	Properties Support Administrator Account Account Enabled: User Name: Authentication Password (8 - 32 Bytes): Confirm Authentication Password (8 - 32 Bytes): Confirm Privacy Password (8 - 32 Bytes): Confirm Privacy Password (8 - 32 Bytes): Confirm Privacy Password (8 - 32 Bytes): Print Drivers / Remote Client Account Account Enabled: Reset to default Password:	International Changes	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	

- 24. Enter SNMPv3 password in all four boxes.
- 25. Click Save Changes.

Page 10 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1

Internet Services Phaser 3610	? Help
Status Jobs CLER DPort9100 DUP (Internet Printing Pro DSMB DEniour (mDNS) DSMB Deniour (mDNS) DSMB Deniour (mDNS) DSMB Deniour (mDNS) Extings Durrint Scoole Cloud Print Courtrint Denose Cloud Print Denose Cloud Print Courtrint Courtrint Denose Cloud Print Courtrint Courtrint	Properties Support Settings have been changed. Restart system for new settings to take effect. Restart Back Back
	xerox 🔊

26. Click Restart.

SNMP v3 is now Enabled.

Page 11 of 11 Xerox / UF Health 3rd Party Private Data Version 1.1