


Xerox ConnectKey Print Driver configurations

This documentation will provide screenshots/instructions on how to setup the Xerox ConnectKey printer queue for the following:


- Default to 1-sided and B/W
- Recommendation on how to optimize for print speed
- Enable Xerox Standard Accounting (User Codes)

These screenshots/instructions apply to the Xerox ConnectKey (CK) print queues, after the driver has been downloaded, extracted, and installed on a server in a server-client environment, or on the client itself if installed in a peer-peer environment, with no print server. These may require administrative rights.


Right click on the printer queue (in this case XTEST) and go to printer properties




Click on the Ports Tab and then click on configure port




Change the Protocol from RAW to LPR, set the Queue Name to 'lp' (lowercase LP), and uncheck both LPR Byte Counting and SNMP Status, if either one are checked (in some cases both may be checked or one or the other). Click OK.




While still in printer properties of the print queue, click on the Advanced Tab then Printing Defaults




In the Printing Options Tab, change from 2-Sided Printing to 1-Sided Printing and click OK.



While still in the Printing Defaults screen, now click over to the Image Options Tab. Enable Xerox Black and White Conversion. Enabling this checkbox defaults the printer queue to default prints in B/W. Click Apply and OK.




While still in printer properties of the print queue, click on the Administration tab. Disable Job Notification. Click OK.




While still in the printer properties of the print queue, click on the Configuration Tab. Here we will enable User codes for printing within the Accounting section. Within the Accounting section, select the dropdowns to reflect the settings below. Click Apply and OK when complete. This will close the screen.

- System: Xerox Standard Accounting
- Mask User ID and Account ID: Enabled
- Print-time Prompt: Always Prompt
- Remember Last Entered Code: Enabled



Right click on the printer queue again (in this case XTEST) and go to printer properties. Within the General tab, click on Preferences.



Here we are only verifying that the defaults we made under the Printer properties> Advanced> Printing Defaults carried over for 1/sided and B/W.

Once verified, we can test.

8/23/2021